



## DOCTOR CHARGE 130 230V 12V/24V



### Overview

#### DOCTOR CHARGE 130 230V 12V/24V

cod. 807599

Electronic BATTERY MANAGER for total maintenance of WET, GEL, AGM, MF, PbCa, EFB and Li batteries at 12/24V and for support activities when intervening on vehicles in workshops, repair shops and car dealer premises.

The innovative Power Stream technology guarantees better performance, up to 50% more than traditional battery chargers.

The Pulse Tronic technology guarantees optimal battery charging over 8 phases.

Doctor Charge 130 carries out 5 functions:

1. automatic charge and maintenance of batteries with PULSE TRONIC technology, even in difficult environmental conditions (low temperatures);
2. battery tests such as voltage at terminals, starting capacity (CCA) and operational check of the vehicle alternator;
3. recovery of sulphated or very discharged batteries, and recovery of optimal operation with periodic regeneration;
4. stable power supply source for battery changes (to protect the on-board electronics), for diagnostic activities (operation checks carried out on the vehicles), for keeping the batteries of display vehicles in showrooms operational;
5. vehicles start.

Based on the SMPS (Switch Mode Power Supply) Technology. In case of black-outs or repetitive uses Doctor Charge 130 can set itself at the last settings carried out.

Many protections available. Fit with PFC device.



1 PH 230V



CE MARKING



EAC CERTIFICATION

### Technical data

<b>CODE</b>	CODE 807599	<b>A<sub>EFF</sub></b>	EFFECTIVE CHARGING CURRENT 140 / 70 A	<b>W<sub>H</sub>L</b>	DIMENSIONS 20 x 26 x 34 cm
<b>V<sub>1PH</sub></b>	SINGLE PHASE MAINS VOLTAGE 230 V	<b>A<sub>EN</sub></b>	RATED CHARGE CURR. EN60335-2-29 120 / 60 A	<b>kg</b>	WEIGHT 6 kg
<b>F</b>	MAINS FREQUENCY 50 / 60 Hz	<b>A<sub>IV/C</sub></b>	START CURRENT 1V/C EN60335-2-29 180 A	<b>BAR CODE</b>	EAN CODE 800489706429 1
<b>P<sub>CHARGE</sub></b>	CHARGE POWER 1,8 KW	<b>C<sub>MIN</sub></b>	MIN. RATED REFERENCE CAPACITY 20 A	<b>PALLET</b>	PIECES/PALLET 30 pz/pallet
<b>P<sub>START</sub></b>	START POWER 2 KW	<b>C<sub>MAX</sub></b>	MAX RATED REFERENCE CAPACITY 1200 A	<b>PALLET</b>	PIECES/PALLET - B 24 pz/pallet-B



**DOCTOR CHARGE 130 230V 12V/24V**



CHARGING VOLTAGE 12 / 24 V



ADJUSTMENT POSITIONS 7

---

**Included Accessories**

null - 125000